

- a) Using the truth table below, create a K-map and solve for a minimal sum-of-products expression.

A	B	C	D	Y
0	0	0	0	X
0	0	0	1	1
0	0	1	0	1
0	0	1	1	1
0	1	0	0	X
0	1	0	1	1
0	1	1	0	0
0	1	1	1	1
1	0	0	0	0
1	0	0	1	0
1	0	1	0	1
1	0	1	1	1
1	1	0	0	X
1	1	0	1	X
1	1	1	0	0
1	1	1	1	1

Here is a grid you can use if desired.


- b) Regardless of whether or not you circled them in the K-map or used them in the SoP expression, are there any **non-essential prime implicants** (of 1s) in this function? If so, what are the expressions that represent them?